
Trans-Data LTE KYZ7,5/8/10 A741031

Full Band Directional Antenna Technical Sheet



Applications

- LTE/CDMA800/GSM/3G/WLAN/Wimax
- Wireless communications and data transmission system 、Repeater
- Indoor and outdoor directional coverage

Features


- Broad band, Stable performance
- Low VSWR, High gain
- Support the popular communications system currently
- Sealed with radome, Strong protection ability
- Supplied with down-tilt bracket kit

Specifications

			and the second s	
Model		Trans-Data		
		LTE KYZ7,5/8/10		
		A741031		
Freq.Range-MHz		698-	800-	1700-
		800	960	2700
Beamwidth	E-o	65	60	50
	Н- °	85	85	60
F/B Ratio-dB		≥15	≥20	≥20
Gain-dBi		7. 5	8. 5	10
VSWR		≤1.5		
Impedance-Ω		50		
Polarization		Vertical		
Max.Power-W		100		
Connector		N female or customized		
Dimensions-mm		293×210×65		
Weight-Kg		0.92		
Mast Diameter-mm		φ40 to 50		
Note: Mhon install	ing vo:	chould make	a tha aida wi	th a little

Note: When installing, you should make the side with a little hole face down to prevent the radome from raining.

Installation Sketch



- 1. Mast(user-provide);
- 3. connector;

- 2. "L" mounting kit;
- 4.antenna

